



AirTap Warm-air Hand Dryer 371

110 V with IR sensor
Deck-mounted
Stainless Steel with satin finish
2-year warranty




DAN DRYER AirTap features a minimalist, modern design in stainless steel with satin finish. The intelligent temperature control technology detects the room temperature and adjusts the heating element.

Application

DAN DRYER AirTap is a powerful hand dryer suitable for toilet rooms with a high visitor frequency. With its elegant slim design, the hand dryer is the perfect choice for all kinds of commercial washrooms. The DAN DRYER Tap range is an ideal build-in solution for construction projects and automatic hand wash stations.

Technical data

	DAN DRYER AirTap
	Prod. No.: 371
Type	Touch-less warm-air hand dryer with IR sensor
Dimensions tap	H 170 x W 50 x D 220 mm
Dimensions motor	H 203 x W 306 x D 150 mm
Material	Stainless steel, satin finish
Drying cycle	10-15 sec.
Connection	110 V, 50/60 Hz, Class I 
Total wattage	600-1000 W
Heating element	100-500 W
Motor	500 W
Noise level	68.5-70.5 dBA
Max. air capacity	84-101 m/sec.
Max. air outlet temperature	57° C
Net weight	6.0 kg
IP rating	IP35

Tender text

Touch-less hand dryer in stainless steel with satin finish for deck mounting. Infra-red sensor and electronic timer, drying cycle: 10-15 sec. IP35, 110 V, 50/60 Hz, 1000 W, Class I (earthed). 68.5-70.5 dBA.

Net weight: 6.0 kg. H: 170 mm, W: 50 mm, D: 220 mm.

Approval

UL, CE, GS, BSMI, EMC, LVD, WEEE, RoHS, UKCA

References

Shopping centres, restaurants, hotels, airports, sports facilities, schools and public institutions.

Standard colour

Stainless steel, satin finish

Activation

Infrared sensor and electronic timer. Touch-free. Activation distance adjustable 130 mm (± 20 mm). Automatic stop after 60 seconds of continuous use.

Motor type

Commutator motor with carbon brushes. 22,000-29,000 revolutions/min.

Protection

Automatic thermal cut-out in both motor and heating element.

Installation

Machine intended for table top mounting. Connection to fixed installation or via circuit-breaker. Installation must be carried out by a qualified electrician.

